



Firmware Upgrade Instructions

Dark Ops Pro Dual Lens Nano Series Camera (BTC-6DCLN)

Latest firmware version: V3.02 (m22111000)

Important

Do not turn the camera off, remove the batteries, eject the battery tray, or allow the batteries to lose power while the firmware is installing. If power is interrupted during the upgrade, the camera may stop working and will need to be returned to the warranty center so the firmware can be reloaded with production equipment.

Before you start, install new alkaline AA batteries in the camera.

Before You Begin

- Use a blank SD card.
- Copy the BTC6DCLN .BIN firmware file to the SD card. Do not open or rename the file.
- Read all instructions before starting the upgrade.
- Keep the camera powered off until the instructions tell you to turn it on.

Upgrade Steps

1. With the camera powered off, insert the SD card containing the firmware file into the camera.
2. Turn the camera on. Do not allow the camera to take a photo or video before starting the upgrade.
3. Press the M button to open the camera menu.

4. Press the Up arrow one time to highlight SW Upgrade, then press M to select it.
5. Use the arrow buttons to change Cancel to OK.
6. Press OK to begin the firmware upgrade.

During the Upgrade

- The display will show Upgrading for approximately 30 seconds.
- Do not turn the camera off.
- Do not remove the battery tray or SD card.
- Do not press any buttons until the upgrade finishes.

When the upgrade is complete, the display will go blank and then return to the Home Screen.

After the Upgrade

The camera will be restored to factory settings. Reset the date, time, and any custom settings before placing the camera back in use.

Need Help?

If you have questions or need help upgrading your camera firmware, contact Browning Trail Cameras Customer Service at 1-888-618-4496, Option 2.